

# Caller ID (MFC-660CN) (For U.K. and Ireland only)

The Caller ID feature lets you use the Caller ID subscriber service offered by many local telephone companies. Call your telephone company for details. This service shows the telephone number, or name if it is available, of your caller as the line rings.

Download and install the latest firmware to add support for Caller ID subscriber services to your machine.

## How to use

You can use a number in the Caller ID history to make a phone call, send a fax, add it to Speed-Dial, or delete it from the history. (See *How to dial from the Caller ID history* on page 2.)

After a few rings, the LCD shows the telephone number of your caller (and name, if available). Once you answer a call, the Caller ID information disappears from the LCD, but the call information stays stored in the Caller ID memory.

- You can see the first 15 characters of the number (or name).
- The # *Unavailable* message means the call originated outside your Caller ID service area.
- The # *Withheld* message means the caller has intentionally blocked transmission of information.

You can print a list of the Caller ID information received by your machine. (See *Printing Caller ID List* on page 2.)



### Note

Caller ID service varies with different carriers. Call your local telephone company to find out about the kind of service available in your area.

## Setting the Caller ID to On

If you have Caller ID on your line, then this function should be set to *On* to display the caller's phone number on the LCD as the telephone rings.

- 1 Press **Menu**.
- 2 Press **▲** or **▼** to choose *Fax*. Press **OK**.
- 3 Press **▲** or **▼** to choose *Miscellaneous*. Press **OK**.
- 4 Press **▲** or **▼** to choose *Caller ID*. Press **OK**.
- 5 Press **▲** or **▼** to choose *On (or Off)*. Press **OK**.
- 6 Press **Stop/Exit**.

## Viewing Caller ID List

If Caller ID is set to *On*, your machine stores information for the last thirty calls in the Caller ID list. You can view or print this list. When the thirty-first call comes in to the machine, it replaces information about the first call.

- 1 Press **Menu**.
- 2 Press **▲** or **▼** to choose *Fax*. Press **OK**.
- 3 Press **▲** or **▼** to choose *Miscellaneous*. Press **OK**.
- 4 Press **▲** or **▼** to choose *Caller ID*. Press **OK**.
- 5 Press **▲** or **▼** to choose *Display ID*. Press **OK**.

The Caller ID list will appear on the display. If no ID is stored, the beeper will sound and `No Caller ID` will appear on the display.


- 6 Press **▲** or **▼** to scroll through the Caller ID memory to view the Caller ID information.

The LCD shows the caller's number and the date and time of the call.

- 7 To finish viewing, press **Stop/Exit**.



#### Note


You can also view the Caller ID list by pressing  (**Fax**). (See *How to dial from the Caller ID history* on page 2.)

## Printing Caller ID List

- 1 Press **Menu**.
- 2 Press **▲** or **▼** to choose `Fax`. Press **OK**.
- 3 Press **▲** or **▼** to choose `Miscellaneous`. Press **OK**.
- 4 Press **▲** or **▼** to choose `Caller ID`. Press **OK**.
- 5 Press **▲** or **▼** to choose `Print Report`. Press **OK**.  
If no ID is stored, the beeper will sound and `No Caller ID` will appear on the LCD.
- 6 Press **Mono Start** or **Colour Start**.
- 7 After printing has finished, press **Stop/Exit**.

## How to dial from the Caller ID history

The last 30 numbers of phone calls or faxes you received will be stored in the Caller ID history. You can choose one of these numbers to telephone, fax to, add to Speed-Dial, or delete from the history.

- 1 Press  (**Fax**).
- 2 Press **▲** or **▼** to choose `Caller ID hist..`. Press **OK**.
- 3 Press **▲** or **▼** to choose the number you want to call. Press **OK**.
- 4 Do one of the following:
  - To make a phone call, press **▲** or **▼** to choose `Make a Phone Call`. Press **OK**.
  - To send a fax, press **▲** or **▼** to choose `Send a Fax`. Press **OK**.
  - If you want to store the number, press **▲** or **▼** to choose `Add to Speed-Dial`. Press **OK**.  
(See *Storing Speed-Dial numbers from the Caller ID history* on page 3.)
  - Press **▲** or **▼** to choose `Delete`. Press **OK**. Press **1** to confirm.




#### Note

You can print the Caller ID list. (See *Printing Caller ID List* on page 2.)

## Storing Speed-Dial numbers from the Caller ID history

---

If you have the Caller ID subscriber service from your telephone company you can also store Speed-Dial numbers from incoming calls in the Caller ID history.

- 1 Press  (**Fax**).
- 2 Press ▲ or ▼ to choose  
Caller ID hist..  
Press **OK**.
- 3 Press ▲ or ▼ to choose the number you  
want to store.  
Press **OK**.
- 4 Press ▲ or ▼ to choose  
Add to Speed-Dial.  
Press **OK**.
- 5 Press ▲ or ▼ to choose the 2-digit  
Speed-Dial location you want to store  
the number in.  
Press **OK**.
- 6 Do one of the following:
  - Enter the name (up to 16 characters)  
using the dial pad.  
Press **OK**.
  - To store the number without a name,  
press **OK**.
- 7 Press **OK** to confirm the fax or  
telephone number.
- 8 Do one of the following:
  - Enter the second fax or telephone  
number (up to 20 digits).  
Press **OK**
  - If you do not want to store a second  
number, press **OK**.
- 9 Press **Stop/Exit**.